



#### Antenna description :

Type	Supplier	Comments	
FPC	HT	LTE B1/B3/B7/B8/B20/B28/B32/B38/B40/B41 WIFI 2.4G/5G	Main antenna

#### Gain

Band	Average Gain(dBi)	Maximum Gain(dBi)
LTE-FDD B1	-2.9	2.6
LTE-FDD B3	-2.4	3.7
LTE-FDD B7	-3.6	2.0
LTE-FDD B8	-3.4	1.4
LTE-FDD B20	-3.8	-1.4
LTE-FDD B28	-4.2	0.8
LTE-FDD B32	-5.5	0.1
LTE-FDD B38	-3.3	2.3
LTE-FDD B40	-3.3	0.5
LTE-FDD B41	-3.2	2.3

### Diversity antenna Gain

<b>Band</b>	<b>Average Gain(dBd)</b>	<b>Maximum Gain(dBd)</b>
LTE-FDD B1	<b>-4.7</b>	<b>0.6</b>
LTE-FDD B3	<b>-3.4</b>	<b>3.8</b>
LTE-FDD B7	<b>-4.9</b>	<b>0.7</b>
LTE-FDD B8	<b>-3.5</b>	<b>1.3</b>
LTE-FDD B38	<b>-4.8</b>	<b>1.3</b>
LTE-FDD B40	<b>-3.8</b>	<b>4.1</b>
LTE-FDD B41	<b>-4.3</b>	<b>2.5</b>

### WIFI ANT1 Gain

<b>Band</b>	<b>Average Gain(dBi)</b>	<b>Maximum Gain(dBi)</b>
2.4G	<b>-4.6</b>	<b>4.5</b>
5G	<b>-4.1</b>	<b>1.4</b>

### WIFI ANT2Gain

<b>Band</b>	<b>Average Gain(dBi)</b>	<b>Maximum Gain(dBi)</b>
2.4G	<b>-1.8</b>	<b>3.1</b>
5G	<b>-2.2</b>	<b>3.6</b>

### WIFI ANT 1+2Gain

<b>Band</b>	<b>Average Gain(dBi)</b>	<b>Maximum Gain(dBi)</b>
2.4G	<b>-0.08</b>	<b>6.81</b>
5G	<b>-0.08</b>	<b>5.55</b>