


TF-T18说明书 成品尺寸：70X100mm 128铜版纸 覆哑膜 钢琴折


TRANSFORMERS


TF-T23真无线蓝牙耳机


使用说明书

包装清单


耳机 \*2


Type-C充电线 \*1


充电仓 \*1


说明书与保修卡 \*1

产品示意图

指示灯

功能键

出音孔

Type-C接口

充电触点

温馨提示

1.除说明书有特殊标示的操作方式以外,请勿尝试拆卸或更换产品内的任何零件。

2.请勿将产品放入水或其他任何液体中,此产品非防水设计。

3.如果有任何液体不小心进入产品内时,请立即断开连接并移开此产品。

4.为避免触电,请在安装或卸载产品时,确保手上没有沾水。

5.请勿将此产品放置于热源附近或直接暴露在火源附近。

6.请勿将本产品放置在有强大电磁力的环境中,否则会导致产品故障。

耳机规格

蓝牙版本: V5.4

传输距离: ≥10m

喇叭直径: Φ13mm

喇叭阻抗: 32Ω±15%


灵敏度: 108±5dB @1kHz

工作频率: 2.4-2.480GHZ

频率响应: 20Hz-20KHz

充电时间: 约1.5/小时


电池容量: 30mAh 3.7V

额定输入: 5V  30mA

充电仓规格

充电时间: 约1.5/小时

电池容量: 280mAh 3.7V

额定输入: 5V  280mA

产品操作说明

①开机:

方法1. 长按耳机功能键3秒。方法2. 从充电仓取出耳机, 蓝灯长亮1秒耳机开机。

(语音提示音: "Power on")

②关机:

方法1.与蓝牙设备断开连接3分钟后, 自动关机。方法2.耳机放入充电仓后, 自动关机

(语音提示音: "power off")

③蓝牙配对:

步骤一: 耳机开机, 左右耳机自动互连后进入配对状态。(语音提示音: "pairing")

步骤二: 打开智能设备的蓝牙列表, 搜索"TF-T23"并连接。

(语音提示音: "connected")

进入设备配对状态:

主耳蓝灯快闪, 副耳熄灭

LED指示灯状态

模式	描述	语音提示
开机	耳机蓝色指示灯亮一秒	"Power on"
关机	—	"Power off"
配对	耳机蓝色指示灯闪烁	"Pairing"
连接	耳机指示灯熄灭	"Connected"
断开	耳机蓝色指示灯闪烁	"Disconnected"
耳机低电	蓝灯每5秒闪烁一次	"Battery Low"
充电仓给耳机充电	RGB指示灯长亮12秒	—
充电仓低电	红色指示灯快闪	—
充电仓充电	红色指示灯慢闪	—
充电仓充满	红色指示灯长亮	—

触摸操作

■ 常规模式

语音助手: 长按左功能键2秒启动/关闭

音量加: 单击右功能键

音量减: 单击左功能键

■ 音乐播放模式

播放/暂停: 双击任意耳机功能键

上一曲: 三击左耳功能键

下一曲: 三击右耳功能键

■ 通话模式

接听/挂断来电: 双击任意耳机功能键

拒接来电: 长按任意耳机功能键2秒

■ 游戏/音乐模式切换

音乐模式: 长按右耳触摸键2秒 (语音提示音"music mode")

游戏模式: 长按右耳触摸键2秒 (语音提示音"game mode")

恢复出厂设置

耳机开机后未与蓝牙设备连接状态下, 连续单击左/右耳机功能键5次清除配对信息后关机

产品中有有害物质名称及含量

部件名称	有害物质					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
印刷电路组件	○	○	○	○	○	○
外壳等小结构件	○	○	○	○	○	○

本表格依据SJ/T11364的规定编制  
O:表示该有害物质在该部件所有均质材料中的含量均在GB/T26572规定限量要求以下。  
X:表示该有害物质至少在该部件的某一均质材料中的含量超出GB26572规定的限量要求。  
表中标记"X"的部件,皆因全球技术发展水平限制而无法实现有害物质的替代。

本表格依据SJ/T11364的规定编制  
印刷电路板组件\*包括印刷电路板及其零部件,电子元器件等。  
根据产品类型不同,您所购买的产品可能不会含有以上所有部件

10

在中华人民共和国境内销售的电子电气产品必须标识此标志,标志内的数字代表在正常的使用状态下的产品的环保使用期限。

保修声明

免责声明

本使用手册没有任何形式的担保、立场表达或其他指示。本使用手册所提到的产品、规格及信息仅供参考,内容亦会随时更新于网页,恕不另行通知。

保修声明:

就本文件附随的产品做如下保证:如产品在您购买日起十二(12)个月(“保修期”)内,在正常使用情况下因质量问题或发生损坏,能修理的,免费修理;经厂家确认无法修理的,免费更换;修理或更换后的产品,在剩余保修期(最短不少于30天)内继续享有保修。购买日以销售发票日期为准;如无法确定购买日,则保修期自产品生产日期起按十三(13)个月计算。

如申请保修,请先致电产品服务热线,并按我们指示的方式执行。申请保修时,您需提供准确、完整和清晰填写的有效销售发票,以上保证不适用于下列情况:

1.超过三包有效期的;

2.涂改保修卡、产品编码与产品本体不符;

3.因误用、滥用或不适当的运输、使用、维护或保管而导致的故障或损坏;

4.因不可抗力(如地震、战争、火灾等)或意外导致的故障或损坏;

5.拉扯、磕碰和因受力过大而损坏;

6.因承载过重造成的脱线或断裂;

7.任何因尖锐物体造成的损坏;

8.有烧损或水渍迹象的产品;

9.因擅自拆改导致的损坏;

10.产品在正常使用过程中发生的老化、褪色、磨损、破裂和其他损耗。

11.如产品原有标识标签被更改或损毁,本保证将失效。

产品及随附物料的齐备和外观完好不属于保证范围,您应在接收产品时当场检验并对任何不符提出异议。

以上保证是我们就产品做出的全部保证,且仅在中国大陆地区境内适用。本文件的任何内容均不影响根据法律规定不能排除或限制的消费者权利。

服务监督热线:400-885-8808

合格证

产品编号: \_\_\_\_\_  
生产日期: \_\_\_\_\_  
检验员: \_\_\_\_\_

虚线做  
易撕线

反面

Warranty Service

Dear user,this warranty card is the proof of your future warranty application,please cooperate with the seller to fill it out and keep it for future use!

User info

User name

Contact number

Mailing address

Email

Postal code

Product information

Product name

Product barcode / Serial number / Batch number

Product number

Vendor information

Name

Address

Contact number


Sales date

Remark

Postal code

Invoice number

Certificate of Approval

Product No.: \_\_\_\_\_  
Production Time:   
QC: \_\_\_\_\_


TRANSFORMERS


TF-T23 True wireless BT headset


Instruction manual


虚线做  
易撕线

Packing list


Headphones \*2


Type-C Charging cable \*1


Charging case \*1


Instructions and Warranty card \*1

Product diagram

Pilot lamp

Touch area buttons

Sound outlet

Type-C interface

Charging contact

Tips

1.Except for the operation methods specifically marked in the manual,please do not try to disassemble or replace any parts in the earbuds.

2.Don't put the earbuds in the water or any others liquid.The earbuds are not waterproof.

3.If any liquid enters the product by accidentally,please disconnect and remove the connection immediately.

4.Please make sure that there is no water on your hands when installing or uninstalling the product to avoid electric shock.

5.Do not put the product near by the heat source or expose it to the fire source directly.

6. Do not put the product in the environment with strong electromagnetic force,otherwise it will cause product malfunction.

Headset specifications

BT version: V5.4

Transmission distance: ≥10m

Horn diameter: Φ13mm

Horn impedance: 32 Ω ± 15%

Sensitivity: 108± 3dB@1kHz


Operating frequency: 2.4-2.480GHZ

Frequency response: 20Hz-20KHz

Charging time: About 1.5 hours

Music time: About 4.5 hours


Battery capacity: 30mAh 3.7V

Rated input: 5V  30mA

Charging bay specification

Charging time: About 1.5 hours

Battery capacity: 280mAh 3.7V

Rated input: 5V  280mA

Product operation instructions

① Boot:

Method 1. Press and hold the earphone touch area for 3 seconds.

Method 2. Remove the earphone from the charging compartment, and keep the blue light on for 1 second to turn on the earphone.

(Voice prompt tone: "Power on")

② Shutdown:

Method 1. Automatically shut down after disconnecting from BT device for 3 minutes

Method 2. After the earphone is put into the charging bin, it automatically shuts down.(Voice prompt tone: "Power off")

③ BT pairing:

Step 1: The headset is turned on, and the left and right headphones are automatically connected to enter the pairing state.

Step 2: Open the BT list of smart devices, search for "TF-T23" and connect.

(Voice prompt tone: "connected")

LED indicator status

Mode	Describe	Sound prompt
Power On	Earphone blue indicator is on for one second	"Power on"
Power Off	—	"Power off"
Pairing	The earphone blue indicator blinks	"Pairing"
Connected	Headphone indicator off	"Connected"
Disconnected	The earphone blue indicator blinks	"Disconnected"
Low Battery	The blue light flashes every five seconds	"Battery Low"
Headphones placed in charging case	The RGB indicator is on for 12 seconds	—
Charging case low power	Red light flashes quickly	—
Charging case charged	The red indicator light flashes slowly	—
Charging case fully charged	Red indicator lights up	—

Touch operation

■ General mode

Voice Assistant: Press and hold the left function key for 2 seconds to start/stop

Volume Increase: Click the right function key

Volume Down: Click the left function key

Next: Three clicks right ear function key

■ Music playback mode

Play/Pause: Double click any headset touch button

Previous: Three hits left ear function key

Next: Three clicks right ear function key

■ Call mode

Answer/hang up a call: Double click any headset touch button

Reject incoming calls: Hold down any earphone touch button for 2 seconds

■ Game/ Music mode switch

Music mode: Press and hold the touch button on your right ear for 2 seconds. (Prompt tone:"music mode")

Game mode: Long press the right ear touch button for 2 seconds. (Prompt tone:"game mode")

Restore factory settings

If the headset is not connected to the Bluetooth device after the headset is turned on, click the left/right headset function key five times to clear the pairing information and shut it down

The name and content of harmful substances in the earbuds

Part Names	Harmful Substances					
	Pb	Hg	Cd	Cr(VI)	PBB	PBDE
Printed circuit assembly	○	○	○	○	○	○
Small structural parts such as shell	○	○	○	○	○	○

This form is compiled in accordance with SJ/T 11364.  
O:Indicates that the content of the hazardous substance in all homogeneous materials of the part is in below the limit required by GB/T 26572.  
X:Indicates that the hazardous substance at least in a certain homogeneous material of the part exceeds The limit requirements specified in GB/T 26572.  
The parts marked with "X" on the form are all harmful due to the limitations of global technological development. Substitution of substances.

Printed circuit board components:  
Including printed circuit boards and their parts,electronic components, etc.and depending on the product model,the earbuds you purchased may not contain all the above components.

10

Electronic and electrical products sold in the People's Republic of China must mark this LOGO,the number in the logo represents the product under normal use Environmental protection use period.

Warranty statement

Disclaimer

This user manual does not have any form of guarantee,position expression or other implication.The mentioned products specifications and information are for reference only,and the content will also be updated on the web at any time without additional separate notice

Warranty statement:

The product attached to this document is guaranteed as follows:If the product is twelve (12) months from the date of purchase("Warranty Period")under normal conditions of use due to quality defects damaged,can be repaired.Free repair,free replacement if the manufacturer confirms that it cannot be repaired; repaired or replaced product.Continue to enjoy the warranty during the remaining warranty period (the shortest not less than 30 days).Purchased by sale the ticket date shall prevail.If the purchase date cannot be determined,the warranty period shall be 15 (15) months.

If you apply for a warranty,please call the product service hotline first and execute it in the manner instructed by us.When applying for warranty,you need to provide an accurate,complete and clearly filled out valid sales invoice.

The above guarantee does not apply to the following situations:

1.Exceeding the validity period of the three packs;

2.Altering the warranty card and product code does not match the product body;

3.Causes caused by misuse,abuse or improper transportation,use,maintenance or storage obstacles or damage;

4.Failure or damage caused by force majeure (such as earthquake,war,disaster,etc.) or accident loss;

5.The zipper and tower buckle are damaged due to excessive force;

6.Disconnection or tearing caused by excessive load;

7.Any damage caused by sharp objects;

8.Products with signs of burning or flooding;

9.Damage caused by unauthorized disassembly;

10.Aging discoloration,abrasion,rupture and other losses that occur during the normal use of the product.

11.If the original identification label of the product is changed or damaged,this guarantee will become invalid.

The completeness and appearance of the product and accompanying materials are not within the scope of the guarantee.You should check on the spot and raise objections to any discrepancies.

The above guarantees are all guarantees we make regarding the products,and are only applicable in mainland China.Nothing in this document affects consumers rights that cannot be excluded or restricted under the law profit.

Service supervision hotline: 400-885-8808

TRANSFORMERS

PDF  
MARK

**FCC Warning:**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

**Caution:** Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 0cm between the radiator and your body.