

折页成品尺寸：80mm x 100mm

用料材质：128g铜版纸

CONTENTS

- 1. WHAT'S INCLUDED
- 2. PRODUCT OVERVIEW
- 3. SPECIAL APP & REGISTER ACCOUNT
- 4. CAMERA ADDING, SETTING AND SHARING
- 5. CAMERA INSTALLATION
- 6. TROUBLESHOOTING

WARM REMINDERS:

- Due to transportation safety requirements, the camera is not fully charged when leaving the factory. Before using for the first time, use the 5V Type-C power adapter to charge the camera. This takes 3-5 hours.
- After removing the screws at the bottom of the camera, remove the back cover and long press the ON/OFF button to turn it on before using, you will hear a prompt sound.
- After the camera has been used for a long time and the battery is low, remove the camera from the mounting bracket and plug the power adapter to charge it. It takes about 7 hours to fully charge. The APP shows the battery level. Or we can connect it with a Type-C solar panel to charge the camera and will not need to take it down for charging.
- If the camera is consuming too much power, please select the "Human Body Filtering" option on the APP which will filter out unnecessary events that cause the camera to frequently wake up, alarm, and record.
- Switch the "Alarm Sensitivity Level" to "High" if some motions are missed and the camera wake-ups, alarms and recordings do not satisfy your needs. The battery consumption will be faster.
- The first user to add a camera is the "Administrator" and has maximum permissions, and other users can only use it through administrator sharing. To change the administrator, you need to first remove the device from the Tuya Smart APP, insert the reset needle included in the screws bag into the Reset hole for 2-5 seconds (heat to the start button), and then the new administrator will open the APP and select "+" to add the camera according to the user guide.

I. WHAT'S INCLUDED

Camera, User Manual, USB Charging Cable, Mounting Bracket, Screw Hole Positioning Stickers.

II. PRODUCT OVERVIEW

1. Microphone, 2. Indicator LED, 3. PIR Sensor, 4. ON/OFF Button, 5. Speaker, 6. Micro USB Charging Port, 7. Bracket port.

III. INSTALL APP & REGISTER ACCOUNT

3.1 Download APP Tuya Smart

(1) For iOS system, please search for "Tuya Smart" in App Store.
(2) For Android system, please search for "Tuya Smart" in the Google Play.

3.2 Register for an Account

(1) Register for an account, using your mobile phone number or email to register.
(2) After successful registration, log in to your account with your password.
(3) If your QR code on your phone is in front of the camera lens at a distance of 15-30cm, You will hear the prompt indicates the QR code is recognized successfully. Click "I Heard a Prompt".
(4) Wait for the connection. It will be finished within 2 minutes.
(5) A page prompts that the adding is successful, click "Done".
(6) Jump to the live streaming page automatically.

IV. CAMERA ADDING, SETTING AND SHARING

4.1 Add Camera to App

(1) Long press the power button of the camera until you hear a music prompt, it indicates the startup is successful.
(2) Click "Add Device" or "+" at the upper right corner of the APP homepage to enter the Add Device page.
(3) Click "Camera & Lock" → Click "Smart Camera (Wi-Fi)".
(4) Click to select the small circle in front of "Make sure the indicator..." and click "Next".
(5) Choose the correct WiFi network and enter the correct password, then click "Next" and you will see a QR code on your phone.
(Note: Please choose 2.4GHz WiFi.)

V. TROUBLESHOOTING

4.2 Adjust Settings

The settings page is as follows. It's mainly about the detailed information and functions of the camera. We can adjust the settings like Sounds, Detection Alarm Settings, etc. according to our own needs.

4.3 Share Camera

First, please inform the other users to download Tuya Smart App, and use their mobile phone number or email to complete the registration, and then send the registered account to you as a shared account.

(1) Click "+" at the upper right corner to enter the settings page.
(2) Click "Share Device".
(3) Click "Add Sharing".
(4) Please use Tuya Smart Account to share the device, or you can share the camera through your software.
(5) Enter the Tuya account of the other users and click the "Done" button.

5. CAMERA CHARGING

Note: When charging the camera, remove the back cover after unscrewing the bottom screw of the camera. When fully charged, the back cover needs to be installed back to the camera.

Use the USB charging cable provided to connect the Type-C port at the bottom of the camera to the power adapter for battery charge. Start charging and see the following instructions of the camera:

LED Prompt	The blue LED flashes when charging.
	The blue LED is on when fully charged.
Charging Time	2 hours (minimum battery to fully charged)

6. CAMERA INSTALLATION

6.1 Test the Wireless Signal

To find where to install the camera, you need to test the wireless signal strength.

(1) To test the wireless signal strength, please keep your camera on real-time stream page and take it with your mobile phone together to the place where you want to install the camera.
(2) If the wireless signal is unstable, move the camera as close to the router as possible.

6.2 Find a Mounting Spot

Hanging the camera 6.6-8.2 feet (2-2.5m) above the ground. This height maximizes the detection range of the camera's motion sensor. Avoid placing the camera towards direct sunlight.

6.3 Install the Camera

The camera can be installed indoors and outdoors.

(1) Make sure power on the camera and then tighten the screws of the bottom plate.

7. TROUBLESHOOTING

1. The camera cannot be connected.

(1) Please check whether you are in a place with good WiFi signal. If the WiFi signal is weak, please move closer for good WiFi signal to connect the camera according to the operation guide. After the camera is connected successfully, then move the camera to the position where you want to fixed.
(2) Please use 2.4G WiFi to connect the camera.
(3) If the connection fails, please insert the reset needle to the Reset hole for 3-5seconds on your camera to reset it, and then try connecting the camera again.
(4) Please check whether you enter the correct WiFi password.

2. Is it normal for howling?

Please keep your phone away from the camera to suppress the noise, or lower your phone's volume.

3. Why there is no sound during two-way talk?

When you talk to the camera, please presshold the "Talk" button. And if you can't hear the camera on your phone, please make sure you have turned on the "Mute" icon on your phone.

4. How do I view video files on the memory card?

View the video on "Playback" in the APP or connect the SD card to the computer to view the video files.

5. Why there is frozen image?

Camera needs a certain upload bandwidth to maintain a stable connection. A 2Mbps or above upload bandwidth for camera and a 2Mbps or above download bandwidth for your phone is recommended.

6. Precautions for camera maintenance.

After using for a long time, if the image gradually blurs, you can wipe the lens with a soft cloth with alcohol to remove the stain, then the image will be clear.

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's RF Exposure guidelines, This equipment should be installed and operated with minimum distance between 20cm the radiator your body: Use only the supplied antenna.