# UGREEN


# **Ugreen Group Limited Bluetooth Audio Adapter**

Test Model: 40762

## English

Thank you for purchasing the UGREEN products. For optimum operation, please read this manual carefully before use.

#### **Product Details**



- 1. Button
- 2. RX Mode
- 3. TX Mode 4. Switch Button
- 5. Micro USB Power Port
- 6. 3.5mm Audio Jack

-1-

-7-

### How It Works

### 1. Transmitter (TX) Mode

Slide the switch button to the TX mode.



- Connect and Pair for the First Time
- 1. Use the provided 3.5mm audio cable to connect this transmitter to your computer or TV. 2. Press the button for 3 seconds to turn on this transmitter. And
- it will enter pair mode with red and blue light alternately flashes. 3. Keep your Bluetooth headphone or speaker in the transmitting range of 10m and turn on your Bluetooth headphone or
- speaker. This transmitter will automatically pair with your device. 4. Play music on your computer or TV and start to enjoy wireless
- 5. When you restart this transmitter next time, it will reconnect
- to the Bluetooth device automatically. 6. Press the button for 3 seconds to turn off this transmitter.

Two-point Connection Function

This transmitter can connect two Bluetooth devices at the same time and we take device A and device B as an example. -2-

- 1. Make sure the distance between two Bluetooth devices should not exceed 5 meters
- 2. Pair this transmitter with device A as mentioned above and TURN OFF device A.
- 3. Double click the button to enter pair mode and turn on device B. This transmitter will automatically pair with device B.
- 4. Turn on device A and this transmitter will re-connect with
- 5. Play music on your computer or TV. Now you can share wireless audio with your friend.
- 6. When you restart this transmitter next time, it will reconnect to this two connected devices automatically.

**Note**: The transmitter can only transmit audio from computer/TV to your Bluetooth headphone/speaker and cannot connect computer/TV to your mobile phone.

#### 2. Receiver (RX) Mode

Slide the switch button to the RX mode











# Connect and Pair

- 1. Put this receiver into the transmit range of 10m/32ft and use the provided audio cable to connect this receiver to your 3.5mm/2RCA headphoneorspeaker.
- 2. Press the button for 3 seconds to turn on this receiver. And it will enter pair mode with red and blue light alternately flashes.
- 3. Enable the Bluetooth function of yourphone and start the search for Bluetooth device. (Please refer to the user manual of your cell phone)
- 4. You will find the "Ugreen-40762E in your cell phone list and select it to pair your phone with this receiver.
- 5. Play music on your phone and start to enjoy wireless audio.
- 6. When you restart this receiver next time, it will reconnect to your phone automatically
- 7. Press the button for 3 seconds to turn off this receiver.

**Note:** If this receiver cannot find a device to pair with within 5 minutes, it will automatically shut down.

Two-point Connection Function

This receiver can connect two phones at the same time and we take phone A and phone B as an example.

1. Make sure the distance between two phones should not exceed 5 meters. -4-

- 2. Pair this receiver with phone A as mentioned above and TURN OFF Bluetooth function of phone A. This receiver will enter pair mode with red and blue light alternately flashes.
- 3. Pair this receiver with phone B as mentioned above.
- 4. Enable Bluetooth function of phone A and this receiver will reconnect with phone A.
- 5. When you restart this receiver next time, it will reconnect to this two connected phones automatically.

**Note:** DO NOT play music on phone A and phone B at the same

### 3. Button Function

- \* Under TX mode, double-click the button to enter the pair. mode if you want to pair with another Bluetooth device.
- $^{\star}$  If you are out the transmit range of 10m for more than five minutes, click the button to re-connect your device when back to the effective range.
- \* Long press the button for 10 seconds and you can reset the unit to factory settings with blue light on for 2.5sec.

#### 4. Charging This Unit

When the red LED indicator starts to flash, you need to charge the unit in time.

-5-

# 1. Charge the unit completely before the first time use.

- 2. Use Micro USB cable (included) and wall charger (not included) to connect this unit to power source.
- 3. When you charge with this unit on, the red indicator stays on all the time and the blue indicator light flashes according to connection status; when you charge with this unit off, the red indicator stays on all the time.
- 4. When this unit is fully charged, the LED indicator will stay blue.

## Safety Notes

- 1. Works with 5V $\pm$ 5% power supply, exceeding range of standard
- 2. The unit should not be placed near the magnet or products with a strong magnetic field, which will affect the normal
- 3. Avoid using this unit in extreme high or low temperatures and humid environments.
- signal interference.
- volume levels for long periods. 6. Do not modify, repair or disassemble the unit, if so, please contact the manufacturer.

- voltage may cause damage to the product or lead to unintended safety problems.
- function of the unit or damage the unit.
- 4. The unit is radio signal. Please make sure there is no other
- 5. To prevent possible hearing damage, do not listen at high

### **Package Contents**

- 1x Bluetooth 4.2 Audio Transmitter/Receiver
- 1x Micro USB Power Cable
- 1x 3.5mm M/M Audio Cable
- 1x 3.5mm female to 2RAC male Audio Cable 1x User Manual

# **FCC Warning**

This device complies with part 15 of the FCC rules. Operation

- is subject to the following two conditions: 1) this device may not cause harmful interference, and
- 2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by

turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- 1) Reorient or relocate the receiving antenna.
- 2) Increase the separation between the equipment and receiver.
- 3) Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- 4) Consult the dealer or an experienced radio/TV technician

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

For latest driver or trouble-shooting service, please feel free contact us via email at support@ugreen.com

Add: Ugreen Building, Longcheng Industrial Park, Longguanxi Road, Longhua, Shenzhen, China Tel: +86-755-28066530

Web: www.ugreen.com

UGREEN is a registered trademark of Ugreen Group Limited. All