

# **Antenna Specification**

Antenna picture	Please refer to the internal photos.		
Antenna Type	Internal inverted F PCB antenna		
Antenna Peak Gain	WIFI&BLE: 2.0 dBi		
Operating Band	2400 MHz ~ 2483.5 MHz		
Test laboratory name and	loT Antenna Test Laboratory, 3 / A,LEEDARSON LIGHTING CO., LTD.		
Address	Xingtai Industrial Park, Changtai Economic Development Zone, Zhangzhou,		
	363900, China		
Antenna Manufacturer	LEEDARSON LIGHTING CO., LTD.		
Model name	M3 pro IPD		
DUT photo	Please refer to the external photos.		
Test Equipment &	SY-16 OTA System		
Calibration Date	2023-02-06		
Test Engineer	O.Young		
Test Date	2023-10-19		

#### 1.1 Test Standard

Antenna	Radiation Efficiency	IEEE Standard Test Procedures for	ANSI/IEEE Std
Performance		Antennas	149-2021

## 1.2 Equipment List:

Equipment	Manufacturer	Model No.	Serial No.	Last Cal.	Due Date
Network Analyzer	Keysight	E5071C	MY46527808	2024/1/9	2025/1/8
Anechoic Chamber	Sunyield	SY-16	SI1727	2023/5/10	2024/5/9

#### 1.3 Test Software: EMQuest

#### 1.4 Test System

The SY-16 OTA system is an anechoic chamber, which can measures antenna passive data such as antenna efficiency, antenna gain, and 2D&3D pattern. The coordinates and topology are shown as follow:




Figure 1 SY-16 OTA system




Figure 2 OTA measurement topology

#### **Test Result**

# Efficiency and Gain

Table 1 Antenna Efficiency and Gain

Frequency (MHz)	Gain (dBi)	Efficiency (dB)	Efficiency (%)
2400	0.53	-4.07	39.19
2410	0.31	-4.22	37.83
2420	0.78	-3.93	40.41
2430	1.05	-3.81	41.63
2440	1.14	-3.82	41.48
2450	1.47	-3.71	42.55
2460	1.67	-3.31	46.69
2470	1.77	-3.16	48.30
2480	1.83	-3.05	49.56
2490	1.97	-2.84	51.97
2500	2.0	-2.63	54.60

## **Radiation Pattern**

Table 2 Product coordinates




Table 3 3D radiation pattern




Table 4 Radiation pattern in XY Plane




Table 5 Radiation pattern in XZ Plane




Table 6 Radiation pattern in YZ Plane

