RM5766-2HD 5" Smart Wi-Fi 1080p



vtech Quick start guide For more support information



Congratulations

on purchasing your new VTech product. Before using this baby monitor, please read the Important safety instructions For support, shopping, and everything new at VTech, visit our website at www.vtechphones.com. In Canada, visit www.vtechcanada.com.

hat does HD Video Monitor do?

VTech 5" Smart Wi-Fi 1080p Pan & Tilt Monitor allows you to stay close to your baby when you are on the move or away. This monitor is Wi-Fi enabled, using your home wireless network to stream live video and audio through the 1080p baby unit and 5-inch color screen parent unit. It allows you to maintain a constant connection to your baby.

You can also monitor from your smartphone and mobile tablet. VTech 5" Smart Wi-Fi 1080p Pan & Tilt Monitor uses MyVTech Baby Plus app to let you instantly see and hear what's happening with your baby from anywhere in the world. The app can be downloaded from the App Store or the Google PlayTM Store. The full HD (1080p) resolution is visible in the app only.

RM5766HD

Pan & Tilt Monitor

When using your equipment, basic safety precautions should always be followed to reduce the risk of fire, electric shock and njury, including the following:

- Follow all warnings and instructions marked on the product CAUTION: Do not install the baby unit at a height above 6.5
- 4. This product is intended as an aid. It is not a substitute for responsible and proper adult supervision and should not be used as such.
- This product is not intended for use as a medical monitor
- Do not use this product near water, for example, near to a bath, sink, swimming pool or shower. . CAUTION: Use only the battery provided. There may be a risk

IMPORTANT SAFETY INSTRUCTIONS

- of explosion if a wrong type of battery is used for the parent unit. The battery cannot be subjected to high or low extreme temperature and low air pressure at high altitude during intending to use it for some time. use, storage or transportation. Disposal of battery in fire or a hot oven, mechanically crushing or cutting the battery can result in an explosion. Leaving the battery in an extremely with the product 24. The small parts of this monitor can be swallowed by babies or high temperature surrounding environment can result in an explosion or the leakage of flammable liquid of gas. Battery
- explosion or the leakage of flammable liquid or gas. Dispose of used battery according to the information in **The RBRC seal**. Use only the power adapters included with this product. correct power adapter polarity or voltage can seriously amage the produc

ubjected to extremely low air pressure may result in an

Power adapter information: Baby Unit Output: 5V DC 1.5A Parent Unit Output: 5V DC 2A VTech Telecommunications Ltd Model: VT07EUS05200

Rechargeable battery information V 5000mAh, 18.5Wh Lithium-ion battery 'huhai Great Power Energy Co., Ltc Model: GSP806090-5Ah-3.7V-1S1P The power adapter is intended to be correctly oriented in a vertical or floor mount position. The prongs are not designed

the-table or cabinet outlet. For pluggable equipment, the socket-outlet (power adapter) should be installed near the equipment and should be easily

to hold the plug in place if it is plugged into a ceiling, under

- 1. Unplug this product from the wall outlet before cleaning Do not use liquid or aerosol cleaners. Use a damp cloth fo 12. Do not modify the power adapters or replace with other
- adapters, as this causes a hazardous situation. 13. Do not allow anything to rest on the power cords. Do not install this product where the cords may be walked on or
- 14. This product should be operated only from the type of power source indicated on the marking label. If you are not sure of the type of power supply in your home, consult your dealer or electricity supply provider 15. Do not overload wall outlets or use an extension cord.
- 16. Do not place this product on an unstable table, shelf, stand or other unstable surfaces. 17. This product should not be placed in any area where proper ventilation is not provided. Slots and openings in the back or bottom of this product are provided for ventilation. To protect them from overheating, these openings must not be blocked by placing the product on a soft surface such as a bed, sofa or rug. This product should never be placed near or over a
- 18. Never push objects of any kind into this product through the slots

because they may touch dangerous voltage points or create a short circuit. Never spill liquid of any kind on the product. The applied nameplate is located at the bottom of the baby unit's ba

o reduce the risk of electric shock, do not disassemble his product, but take it to an authorized service facility Disassembling or removing parts of the product other than via the battery door may expose you to dangerous voltages or other risks. Incorrect reassembling can cause electric shock

vhen the product is subsequently used 20. You should test the sound reception every time you turn on e units or move one of the components

Periodically examine all components for damage. There is a very low risk of privacy loss when using certain electronic devices, such as baby monitors, cordless elephones, etc. To protect your privacy, make sure the

product has never been used before purchase, reset the baby monitor periodically by powering off and then powering on the units, and power off the baby monitor if you are not

Children should be supervised to ensure that they do not play

mall children. Keep these parts out of reach of children. The product is not intended for use by persons (including or lack of experience and knowledge, unless they have been given supervision or instruction concerning use of the ppliance by a person responsible for their safety.

SAVE THESE INSTRUCTIONS

Use and store the product at a temperature between 32°F (0°C) and 104°F (40°C).

- Mishandling batteries can cause burn, fire or explosion Batteries should not be exposed to excessive heat such as bright sunshine or fire.
- Do not expose the product to extreme cold, heat or direct unlight. Do not put the product close to a heating source.
- Warning—Strangulation Hazard—Children have STRANGLED in cords. Keep this cord out of the reach of children (more than 3 ft (0.9m) away). Do not remove warning label on the adapter cord. Never place the camera unit(s) inside the baby's crib or pen. Never cover the camera unit(s) or parent unit with

inything such as a towel or a blanket.


Other electronic products may cause interference with your camera unit. Try installing your camera unit as far away from hese electronic devices as possible: wireless routers, radios personal computers, kitchen appliances and cordless

Precautions for users of implanted cardiac pacemakers c pacemakers (applies only to digital cordless devices ess Technology Research, LLC (WTR), an independent research entity, led a multidisciplinary evaluation of the nce between portable wireless devices and implanted Administration, WTR recommends to physicians that:

- Pacemaker patients keep wireless devices at least six inches from the
- Should NOT place wireless devices directly over the WTR's evaluation did not identify any risk to bystanders with Electromagnetic fields (EMF)
- This VTech product complies with all standards regarding electromagnetic fields (EMF). If handled properly and according to the instructions in this user's manual, the product is safe to be used based on scientific evidence available today.

WHAT'S IN THE BOX

Your baby monitor package contains the following items. Save your sales receipt and original packaging in the event warranty service is necessary.



2 sets for RM5766-2HD

For mobile access:

MyVTech Baby Plus mobile app	
------------------------------	--

Network	Wi-Fi
Wi-Fi router	2.4GHz 802.11 b/g/n
Internet connection	1.5 Mbps @ 720p or 2.5 Mbps @1080p upload bandwidth per baby unit

2. Go to > 🗐 🗀 3. Scan the QR code in below or search the app with keyword "myvtech baby plus" to

DOWNLOAD APP FOR MOBILE ACCESS

Download the free MyVTech Baby Plus mobile app and install it to a

mobile device, then use your mobile device and the mobile app to

download the app into your mobile device if you have not installed the app yet. 4. Follow the instructions in the mobile app to set up and pair your baby unit to the

Alternatively, you can download the mobile app from the App Store or Google Play

Install MyVTech Baby Plus mobile app

1. Press MENU/SELECT when the parent unit is idle.

monitor your baby remotely.

- 1. Browse the App Store 🙆 or the Google Play store 🖭.
- 2. Search for the mobile app with the keyword "myvtech baby plus".
- 3. Download and install the MyVTech Baby Plus mobile app to your mobile device.

Scan the QR codes on the right to get the app.

NOTE

• Make sure your mobile device meets the minimum requirement for the mobile app.

Minimum requirement


The mobile app is compatible with: Android[™] 6.0 or later; and

- iOS 12 or later.

After installing the mobile app, follow the instructions in the mobile app and parent unit to set up and pair your baby unit. In your mobile device:

- 1. Tap to run the mobile app in your mobile device, and then create a user account. 2. We recommend that you use common webmail services, such as Google Gmail for
- registration of your user account. Check your email (and Spam folder), and activate your new camera account via the email verification code, then sign in to your account.
- 3. Follow the instructions in the mobile app to pair the camera.

OVERVIEW



• Red is steadily on when the baby unit is connecting to the parent unit. Red flashing slowly during video streaming In Wi-Fi signal connection:

In direct signal connection:

- O- Night Light Control Key

• Allow you to see clearly in a dark environment.

• Go to **Night Light** section to learn more.

connected to Wi-Fi. Green flashes slowly during video streaming

• Green is steadily on when the baby unit is

ON/OFF switch

Power it on or off.

Speaker 10 Temperature sensor

Light sensor

Camera lens

Infrared LEDs

Microphone

Night Light

LED indicator

- 11 Power jack
- Wall mount slots
 - The parent unit and baby unit provided are already paired.


TALK / 🗢

MENU | SELECT

 Press to enter the main menu. · While in a menu, press to choose an

item, or save a setting.

Parent unit overview



LINK LED light

• On when the parent unit is linked to the baby unit. Flashes when the link to the baby unit

IIII LED light

- On when the parent unit is connected to AC power, and the battery is charging.
- Flashes when the parent unit battery is low and needs to be charged.

3 3- level sound indicator light Green: low sound level is detected by

- the baby unit. • Green and amber: moderate sound
- level is detected by the baby unit. Green, amber and red: high sound level
- is detected by the baby unit.

11 Antenna • Press and hold to talk to the baby unit.

- 12 Speaker • While in a sub-menu, press to exit.
 - 13 Power jack
 - 14 RESET
 - Force reboot the parent unit.

Press to navigate leftward, upward,

main menu and sub-menus.

downward.

Microphone

VOL - | VOL +

volume.

help menu.

10 U Power | LCD ON/OFF

· Press to zoom in/out.

① Zoom

rightward or downward, within the

Press to move the baby unit camera


leftward, rightward, upward or

Increase or decrease parent unit

While in a sub-menu, press to view the

15 Stand

CABLE MANAGEMENT







TECHNICAL SPECIFICATIONS


rrequeriey	Daby ann. 2412 2402 Milit	
Channels	11	
LCD	5" Color LCD (IPS 1280x720 pixels)	
Nominal effective range	Maximum power allowed by FCC and IC. Actual operating range vary according to environmental conditions at the time of use.	
Power requirement	Baby unit power adapter: Output: 5V DC, 1000mA. Parent unit power adapter: Output: 5V DC, 2A. Parent unit battery: 3.7V 5000mAh, 18.5Wh Lithium-ion battery	


Baby unit: 2412 - 2462 MHz


DISCLAIMER AND LIMITATION OF LIABILITY VTech Communications, Inc. and its suppliers assume no responsibility for any damage or loss

resulting from the use of this user's manual. VTech Communications. Inc. and its suppliers assume no responsibility for any loss or claims by third parties that may arise through the use of this product. Company: VTech Communications, Inc. Address: 9020 SW Washington Square Road - Ste 555 Tigard, OR 97223, United States Phone: 1 (800) 595-9511 in the U.S. or 1 (800) 267-7377 in Canada









IOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license.



How the system works

radiator or heat source.

Your baby monitor parent unit and baby unit connect to each other in Direct mode by default, which allows you to immediately stream video out of the box.

CETIP To receive product firmware updates, this baby monitor requires connecting to



You may experience reduced signal strength if your parent unit and baby unit are far apart, or there are obstructing factors, such as internal walls, between them. Move the parent unit closer to the baby unit to improve the signal strength

Local access

Wi-Fi signal connection

in Wi-Fi signal connection to enjoy live video streaming via your mobile app with an enhanced connection.

network to connect your video monitor. It supports live video streaming through the mobile app.

To stream live video remotely with your mobile device, download, install the MyVTech Baby Plus mobile app. With the mobile app, your Wi-Fi router (not included) provides Internet connectivity to your HD video monitor system. It

device, allowing you to monitor and/or control your baby unit wherever you are. For more details, see **Download app for mobile access** section in this quick start quide.

optimised to deliver the best possible viewing result.

VTech cares about your privacy and peace of mind. That's why we've put together a list of industry-recommended best practices to help keep your wireless connection private and your devices protected when online. We recommend you carefully review and consider

- Before installing a device, ensure your router's wireless signal is encrypted by selecting the "WPA2-PSK with AES" setting in your router's wireless security menu.
- Change your wireless router's default wireless network name (SSID) to something unique.
- Change default passwords to unique, strong passwords. A strong password: - Is at least 10 characters long.
- Does not contain dictionary words or personal information.
- Contains a mix of uppercase letters, lowercase letters, special characters and numbers.
- Download security patches from manufacturers as soon as they become available. This will ensure you always have the latest security updates
- If the feature is available, enable automatic updates for future releases.
- A virus or other malware program could use this function to compromise security for the

1. Federal Communications Commission: Wireless Connections and Bluetooth Security Tips

Internet -

4. Wi-Fi Alliance: Discover Wi-Fi Security -

http://www.wi-fi.org/discover-wi-fi/security.

3. Federal Trade Commission: Using IP Cameras Safely – https://www.consumer.ftc.gov/articles/0382-using-ip-cameras-safely.

www.fcc.gov/consumers/guides/how-protect-yourself-online.


CONNECT, CHARGE AND POWER ON THE BABY MONITOR

App Store Get IT ON Google Play

■ Notes

Connect the baby monitor

- Use only the power adapters supplied with this product.
- Make sure the parent unit and the baby unit are not connected to the switch controlled electric outlets. Connect the power adapters in a vertical or floor mount position only. The adapters' prongs are not
- under-the-table, or cabinet outlets. Otherwise, the adapters may not properly connect to the outlets. Make sure the parent unit, the baby unit and the power adapter cords are out of reach of children.




and then turn off after a short time.

After powering up, the baby unit status LED will turn on

Camera lens and surface may get

warm during normal operation.





Charge the parent unit battery before use

The parent unit runs on rechargeable battery or AC power. To continuously monitor your baby, keep the parent unit connected to AC power.

- Before using the baby monitor for the first time, charge the parent unit battery for 12 hours. When
- The parent unit turns on automatically after connecting to the power socket, and the welcome screen appears. You can press **O Power** o turn the parent unit on or <u>press and</u>



BATTERY INDICATORS	BATTERY STATUS	ACTION
and are displayed on the screen; The red LED light flashes.	The battery has very little charge and may be used for only a short time.	Charge without interruption (about 30 minutes).
The battery icon segments are solid [].	The battery is fully charged.	To keep the battery charged, connect it to AC power when in use.



PARENT UNIT ICONS


Monitoring mode (* For RM5766-2HD only) · View baby units in Single mode. View baby units in Patrol mode.

View baby units in Split screen

Turn on or turn off night light

Adjust night light brightnes · Set the brightness to Auto adaptive

Set the timer to turn off night light after 15. Melodies and soothing sounds Play or Stop the Iullaby.



Camera Volume Adjust the play volume level.

Set the timer to stop playing after 15, 30 or 60 minutes, or play non-stop.

Camera Volume

 Adjust Parent Unit screen brightness Screen Off Timer

 When Auto is selected, the parent unit will turn on if the sound exceeds the se sensitivity level.

Temperature Format Change temperature display format

· Reset settings, Software update

70° F Temperature

Battery level indicator Low battery indicator

Temperature alert is turned on. □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □
 □

RM5766-2HD only).

Night vision is turned on.

Night light is turned on.

Motion detection alert is turned on.









a 2.4GHz home Wi-Fi network.

It uses your 2.4GHz home Wi-Fi

serves as a communicating channel between your baby unit and mobile

When both parent unit and app are viewing the camera simultaneously, the video quality will be

PROTECT YOUR PRIVACY AND ONLINE SECURITY

complying with the following tips. Ensure your wireless connection is secure.

Change default settings.

Is complex.

Keep your devices up to date.

Disable Universal Plug and Play (UPnP) on your router. UPnP enabled on a router can limit the effectiveness of your firewall by allowing other network devices to open inbound ports without any intervention or approval from you.


For more information on wireless connections and protecting your data, please review the following resources from industry experts

2. U.S. Department of Homeland Security: Before You Connect a New Computer to the www.us-cert.gov/ncas/tips/ST15-003.




· The rechargeable battery in the parent unit is built-in

designed to hold the weight of the parent unit and the baby unit, so do not connect them to any ceiling,



Slide the power switch to power on your baby unit.





Raise the parent unit antenna for better

the parent unit battery is fully charged, the battery icon segments are solid [.....]. · The standby time varies depending on your actual use.



The battery icon indicates the battery status (see the following table).

Main Sub-Menu menu Options

Main Sub-Menu menu Options **Alerts Settings**

> Turn on/off motion detection alert Adjust Motion Sensitivity Level to

Turn on/off temperature detection alert Select maximum and minimum temperature for alert range. ow battery Turn on/off low battery alert

Turn on/off lost link alert

Status icons A Direct signal connection

How-to Video

Support video

Baby unit 1 and 2 are being viewed in **Patrol** mode (For **RM5766-2HD** only).

Baby unit 1 and 2 are being viewed in **Split** mode (For

Melodies and soothing sounds are playing.

Parent unit, baby unit 1 and baby unit 2 (*For RM5766-**2HD only**) are connected to each others directly. Red bars indicate no connection. Wi-Fi signal connection The signal icon(s) on the left indicate that baby unit 1

and baby unit 2 (*For RM5766-2HD only) are connecte o home Wi-Fi network. The red icon(s) indicates no The parent unit always connect directly with baby unit(s Instructions for adding Baby Unit(s) to Its signal strength indicated by the direct signal connection

Adjust Baby Unit speaker volume Screen Brightness

> The parent unit screen will turn off after ne selected time to save energy. You can still hear your baby while the screen

Auto night light brightness is activated.