DISPLAYS2GO

DISPLAYS2GO DIGITAL 43inch Floor Standing Digital Signage, Non Touch 43inch Floor Standing Digital Signage, IR Touch

Model: DF043NLB,DF043TLB Description: 43inch Floor Standing Digital Signage, Non Touch 43inch Floor Standing Digital Signage, IR Touch

Scan QR code to visit the product page:



Operating Instructions for Digital Signage

Note: Before using the product, please read the instructions carefully! Do not attempt to disassemble this product. If the product does not work properly, please call our Customer Service Department at 1-844-221-3393.

Features	3
Safety Warnings and Precautions	3
Assembly and Connection	5
Packing List	5
Interfaces	6
HDMI Input Feature	6
Steps for Unpacking	7
Wheel and base installation steps	8
Remote Control	9
Description of Basic Operation 10	0
Power on/Standby10	0
About Launch Desktop10	0
Description of Wallpaper Switch	0
File Manager1	1
Local Settings1	1
Status of Menu bar12	2
Screen Rotate1	3
Choose System Language14	4
Factory Reset1	5
DiViEx APP Introduction	6
System requirements	6
How to upload media files10	6
Setting1	8
Edit picture1	8
Music2	1
Technical Specifications	2
Troubleshooting	4
Cleaning and Maintenance	6
Names and Contents of Toxic and Hazardous Substances or Elements in the Product	7
FCC STATEMENT	8

Contents

Features

- 1. Embedded with Android 11 smart operating system and unique UI design, bringing you a more convenient operation and better visual experience.
- 2. Support USB mouse and keyboard, realizing easy manipulation like a computer. Using a mouse for set up is recommended.
- 3. Built-in Wi-Fi module, high capacity memory and high capacity cache, making it smoother to watch 1080P HD movies and play big games.
- 4. High-quality LCD screen as the display, no flicker, low radiation, greatly reducing eye fatigue, eye protection, high brightness, high contrast, and wide viewing angle, ultra-fast response time greatly reduces ghosting of fast moving images.
- 5. Progressive image processing and industry-leading motion compensation technology improve the flickering and blurring in the edges of motion picture.
- 6. Dynamic contrast technology can significantly improve the clarity and contrast of various screens.
- 7. Multi-channel USB interfaces, supporting HD media streaming.

Safety Warnings and Precautions

Thank you for purchasing the high-performance multi-functional LED backlight Digital Signage from Displays2Go. We have considered the factors to ensure personal safety in product design and have tested rigorously at the factory. However, improper installation and use may result in electric shock and fire. In order to safely use, maximize performance of the unit and extend the life of the product, please read and follow all instructions carefully before using the product.

Keep the instructions for future reference.

We strongly recommend using a surge protector, or a power strip with internal circuit breaker to prevent damages to the digital signage.

Symbol Legends:

- ▲ Warning: May cause personal injury or death
- S The operation is prohibited
- ▲ Caution: May cause damage or property loss

If any of the following occurs:

- Power outage or instable voltage.
- Abnormal sound or smell from the unit.
- AC power cord is damaged.
- Digital Signage is damaged due to drop, knock or impact.
- Any liquid or foreign matters fall into the enclosure.



Turn off the Digital Signage immediately, pull out the plug from the power outlet, and ask the authorized personnel for maintenance timely.

S If coal gas or other flammable gas leaks, do not pull out the plug of the LCD Digital Signage or other electrical appliances, instead, turn off the gas valve immediately, and open the doors and windows quickly.



A warning

- Solution Not the power supply before connecting or disconnecting any cables.
 - Do not place the Digital Signage on any instable positions, or else it may be damaged or cause fire.
 - Do not place the Digital Signage in the positions such as:
 - 1. The environment subject to direct strong sunlight, moisture, extreme temperature or too much dust,
 - 2. The environment with flammable or explosive materials,
 - 3. The environment with flammable or corrosive gases,
 - Do not use damaged or inappropriate power outlets, and ensure that the plugs and outlets contact properly.
 - Do not let dust or metal deposits adhere to the plugs and outlets.
 - Do not damage the power cords:
 - 1. Do not modify the power cords,
 - 2. Do not place heavy objects on the power cords,
 - 3. Keep the power cords away from heat source,
 - 4. Do not pull the cord to remove the plug.
 - Do not connect too many plugs to one outlet in parallel, or else it may cause fire due to excessive power consumption.
 - Do not approach the Digital Signage with open flame (e.g. a lighted candle), or else it may cause electric shock or fire.
 - Do not put any sharp objects, metal or liquid into the vents or let them touch the signal terminals to avoid short circuit, product damage, and electric shock.
 - The openings in the enclosure are designed for ventilation and cooling, to ensure long time reliable running of components inside the enclosure and prevent overheating. Do not block the openings when place the unit.

No not touch the plugs with wet fingers, or else it will cause electric shock.

Do not use the Digital Signage in stormy weather, especially when there is lightning, instead, please disconnect the power and antenna plugs to avoid lightning strike.

 ∞ Do not disassemble the Digital Signage without permission, or else it may cause electric shock or fire. Please ask qualified technician for repair.

- Do not let children climb onto the Digital Signage.
- Keep the small parts away from children to prevent them from swallowing.
- If the Digital Signage won't be used for a long time, please turn it off and pull out the power plug.
- To adjust the position of the Digital Signage, please disconnect all power cords and move slowly to avoid tip over.
- Do not scratch or knock the LCD with hard object, or twist and squeeze the LCD.
- Do not turn on the unit immediately when it is moved from a place with low temperature to high temperature, or else it will cause condensation and malfunction.
- Before cleaning the Digital Signage, please pull out the power plug, wipe with soft cloth, do not use industrial chemicals, prevent foreign matters from entering the machine. Improper cleaning (such as cleaning solution, water) may damage the product, erase the printed information, and even cause damage of the components if fluid flows in, resulting in machine failure.
- If the unit displays the same screen for a long time or the moving picture has fixed text or icon, it will leave ghosting on the screen and won't disappear when the unit is turned off, it is normal and isn't covered by the warranty.
- The power of the Digital Signage can be cut off by pulling out the plug.
- If the LCD screen ruptures and the liquid splashes on the skin, please rinse for 15 minutes with clean water immediately, and consult your doctor.
- To carry the Digital Signage with hands, please grab and hold the edges, do not apply pressure on the panel.
- Use the Digital Signage properly: Use in proper lighting conditions, insufficient lighting or long time watching will impair your eyesight.
- Unplug device to disconnect from power.
- Insert the plug into the outlet properly, or else it may cause sparks and fire.
- The technical specifications printed herein and on the packaging are subject to change without prior notice. The Manual may be slightly different from actual operation, and the latter is applicable.

Assembly and Connection

Packing List


Name	Quantity
Digital Signage	1
Remote Control	1
Кеуѕ	2
Cleaning Kit Towel and Glove	1
Base screw package	
L-Shaped Wrench (1)	1
Hex Screws M10*30 (8)	
Shim M10(8)	

Name	Quantity
Operation Manual	1
Power Cord	1
WIFI Antenna	1
Touch Pens(Touchless products do	n
not provide touch pens)	Z
Wheel screw package Cross screwdriver (1) Cross head pad screw M6*12 (16)	1

Note:

Contact Displays2Go if you have questions about the operation, debugging and connection of the unit, if the unit doesn't work normally, please cut off the power immediately and consult the dealer. The unit is class-A product, which may cause radio

interference in living environment. In this case, please take feasible measures, and use power plug as the disconnection device.



1. USB interface * 3, 2. RJ45 interface(Ethernet), 3. HDMI input, 4. Socket, 5. Switch, Note: Please pull out the power plug before installing or disassembling the unit!

HDMI Input Feature

- 1. Connect another media player or PC via HDMI Port on the device.
- 2. Click the Main Apps button "min in the Home page to enter the "APPS" menu interface (Fig. 1),
- 3. Click the "HDMI in" (Figure 2)
- 4. Figure 3 shows the display interface of connecting laptops.

Note: Some media players may not be supported






Fig. 2

Fig. 3

Steps for Unpacking

1. Open the top cover as shown in Fig. 2,





Fig. 1


Fig. 2

1. Take out the base from the package as shown in Fig. 3,

2. Carefully lift out the unit as shown in Fig. 4 and place it on the shipping box (avoid scratching), the unpacking is completed, as shown in Figure 5.

















Wheel and base installation steps

1. Install 4 casters in the corresponding holes at the bottom of the base (Fig. 2), so that the casters are installed on the base (Fig. 3). Tighten all casters with the supplied screwdriver.



2. Connect the base screws to the product base and the product body, and tighten all the base screws with an Allen wrench.







Fig. 4 3. The assembly is finished:





NOTE: Casters can be locked for safety.

Installing batteries for the remote control:

Remove the battery cover and insert two AAA batteries (1.5V). Ensure that the battery polarity matches the "+"/"-" marks in the battery compartment of the remote control.

Precautions for using the remote control:

- Aim the remote control at the receiver window. Do not place any object between the remote control and the receiver window to avoid interference with the normal operation.
- Keep the remote control away from violent vibration. In addition, do not set or place the remote control in direct sunlight, or else the remote control may be deformed by heat.
- The remote control may be invalid when the receiver window of the unit is in direct sunlight or strong lighting, in this case, please adjust the angle of the lighting or the unit or approach the receiver window to use it.
- The distance of remote control will be shortened if the battery voltage is insufficient, in this case, please replace with new batteries, if the remote control won't be used for a long time or the batteries are run out, please take out the batteries to avoid corrosion due to battery leakage, which will damage the remote control.
- Do not use batteries of different types or mix new batteries with old ones. Always replace the batteries in pairs.
- Do not put the batteries in fire, or charge or disassemble them, or charge, short circuit, disassemble, heat or burn used batteries. Please dispose of waste batteries in accordance with local environmental regulations. Do not expose the batteries in overheated environments such as sunlight and fire.

Description of remote control buttons:



Button	Function
Ģ	Power switch
€	To show the Source menu
弦	Mute
4 -	Turn up the volume
1	Turn down the volume
ОК	Confirm selection
	To move the cursor up
▼	To move the cursor down
<	To move the cursor left
	To move the cursor right
Ξ	Switching options
*	Home button
	Go back to the parent menu
MENU	To show the main menu
SETUP	To set up OSD menu

Note: Press the SETUP button in the main interface to call out the OSD menu. After exiting the playback mode by pressing the STOP button, the playback will start according to the schedule next time. **Remark:** The real appearance of the remote control may be different from the picture, please refer to the actual product.

Description of Basic Operation

Power on/Standby


Insert the power plug into the outlet. If the Digital Signage has the switch button "I", turn it on, if you press the switch button "O", the Digital Signage enters standby state.

In power on state, enter "System Assistant" and press the " \bigcup " button on the remote control, and the Digital Signage enters standby state.

About Launch Desktop

Description of Desktop Icons

lcon	Function
Ð	Main applications
•	Sound -
•	Back
	Home page
	Background applications
40	Sound +



Description of Wallpaper Switch


We suggest using a mouse to change the wallpaper.

Connect a mouse with the digital panel through USB port, then follow the steps below:

- 1. click "Setting"
- 2. At the setting menu, click "Display"
- 3. At the Display setting menu, click "Gallery", or "Wallpaper"
- 4. Then select an image you would like to set up as background.
- 5. Confirm the selection by clicking "Set wallpaper".

File Manager

- 1. Click the Main Apps button " (iii)" in the Home page to enter the "APPS" menu interface (Fig. 2),
- 2. Click the "Explorer" icon in the "APPS" menu interface (Fig. 2) and enter "Explorer" menu (Fig. 3),
- 3. Click options in the "Explorer" menu to read the files from different devices.



Local Settings

- 1. Click the Main Apps button "()" in the Home page to enter the "APPS" menu interface (Fig. 1)
- 2. Click the "Settings" icon in the "APPS" menu interface (Fig. 2) and enter "Wi-Fi" menu (Fig. 3),
- 3. Click options in the "Wi-Fi" menu and set up different options.






Fig. 3

lcon	Function
0·	Network & internet
60	Connected devices
<u></u>	Apps & notifications
0	Display
49	Sound
	Storage
ę.	Privacy
0	Location
0	Security
	Accounts
Ť	Accessibility
Ø	Screenshot
۲	Memory
0	System
	About table

Description of Settings Interface (shown on the right)



Status of Menu Bar

- 1. Click the "setting" (Fig. 1),
- 2. Click the "Display" (Fig. 2),
- 3. Open the drop-down box for advanced options (Fig. 3),
- 4. The display interface of the hidden menu bar is shown in Figure 4,
- 5. Click the button on the right to open the display navigation (Fig. 5).




Fig. 4 Fig. 5	14.444			-
	A (1999)		 Anite 	
	And and a second s		100 C C C C C C C C C C C C C C C C C C	
		1.00	Section and the section of the secti	14
			hereine glasse	
	- The second sec		del con	
			To be adjusted	12
		1.10	Add and finds	
			10-1 10-1	
			F 8-	
			ABDs 10	
	and the second s		Testin Tran	
	the second se		All series and the series of t	
(4) (4) (4) (4)	-			
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
(4) (4) (4) (4)				
			Fig. F	

Screen Rotate

- 1. Click the Main Apps button "()" in the Home page to enter the "APPS" menu interface (Fig. 1)
- 2. Click "System assistant" into Fig. 2
- 3. Choose the degree you would like to Rotate screen(Fig. 3), then click "CONFIRM", after the restart, the screen will be rotated (Fig. 4)






Fig. 4

Choose System Language:

- 1. Get into "System" (Fig. 1), then click "Language & input" (Fig. 2)
- 2. Click "Languages", then click "Add a language" (Fig. 3)
- 3. You can add the required system language (Fig. 4)
- 4. Drag the system language you just added up to the front(Fig. 5)






Fig. 4

Fig. 5

Factory Reset:

- 1. Get into Settings, then click "System" (Fig. 1),
- 2. Open the drop-down box for advanced options (Fig. 2),
- 3. Click "Reset options" (Fig. 3),
- 4. Click "Erase all data (factory reset)" (Fig. 4),
- 5. Click "Erase all data" (Fig. 5).



	 118.0 	
·	4	
and the process of the second		
The state of the second		
		Grassi all data Cacitory receill
•		
		10mm
Fig. 4		Fig. 5
8		
DiViEx APP Introd	luction	>

System requirements:

Step 1: Before using this application, make sure your machine meets or exceeds the following system requirements:

CPU	RK3568
ROM	32GB
Operating system	Android 11

How to upload media files :

Step 2: Make new directory named "MediaFolder" in root directory in U disk.

Name	Dete modified	Type
MediaFolder	2020/3/13 16:46	File folder


Open "MediaFolder", create 3 subfolders, and change their names to "Images", "Videos", "Music". Copy the media file to be displayed, image to "Images", video to "Videos", Music to "Music"

Name	Date modified	Type
Images	2020/3/13 16:48	File folder
Music	2020/3/13 16:51	File folder
Videos	2020/3/13 16:51	File folder

Format requirement:


· · · · · · · · · · · · · · · · · · ·		
Image	JPG/JPEG/BMP/PNG	
Video	MPEG1/MPEG2/MPEG4/ MKV	
Music	MP3	

Step 3: Plug in the USB drive into the device and click the DiViEx App to open it.



ALC: NOT REAL PROPERTY.

Step 4: When the screen shows "Copy finished" after "Usb Disk: ",



Setting:

Step 1: Select the time you would like each picture to be on the screen for by dragging the bar to the desired time. Select how you would like the images to display. Select the desired transition effect between pictures.

• Auto Boot

If enable, application will auto boot when android system boot

• Auto Play

If enable, application will show all resource including images, videos

• Choose Picture display mode

"Adapt", "Center", "Reshaped by the original size", "Set Image center adaptation display"

• Set Picture switch mode

During the image conversion process, there are 10 animations: "Normal", "Depth", "Zoom", " Cubeln", "Foreground To Background", "Flip3D", "Filp Horizontal", "Rotate Down", "Accordion, Stack".



Edit picture:

This function show all pictures, you can edit all pictures, and remove it.

• Edit picture (Crop)

There are four corners and four border to crop the picture, you can drag it

• Text

You can add text to the picture

• Filter

Set different filter for the picture, we support the following filter: NOE, AUTO_FIX, BRIGHTNESS, CONTRAST, DOCUMENTARY, DUE_TONE, FILL_LIGHT, FISH_EYE, GRAIN, GRAY_SCALE, LOMISH, NEGATIVE, POSTERIZE, SATURATE, SEPIA, SHARPEN, TEMPERATURE, TINT, VIGNETTE, CROSS_PROCESS, BLACK_WHITE, FLIP_HORIZONTAL, FILP_VERTICAL, PSTERIZE, ROTATE.



• Sticker

You can add seven special effects to the picture



Frame

You can add different borders to the picture



Reset

Restore the original image

Picture sharing " < "
 When you click the share button, you can share the picture to the corresponding APP




• Pictures saving "

When you click the Save button, it will create a new picture



Image deletion


Click "
"
to delete unwanted pictures



Music:

List all music files in Playlist library

- Add music to playing list music from Playlist library, you can click right arrow, music title will show the number of playlist music.
- To remove background music from the playlist, click the left arrow in the playlist





Technical Specifications

	ITEM	SPECIFICATION			
	LCD size	43"			
-	Light source	LED backlight			
	Resolution	1920*1080 (pixels)			
	Brightness	400cd/m ²			
	Contrast	1200: 1			
	Response	10ms			
Panel	Pixel pitch	0.16 (H) * 0.49(V) mm			
	Refresh rate	60Hz			
	Viewing angle	178° (H)/178° (V)			
	Color saturation	72%			
	Viewable area	940.9 (H) * 529.3 (V) mm			
	Chromaticness	16.7M			
	Voltage	100V~240V, 50-60Hz			
Power supply	Power Consumption	≤95W			
	Operating temperature	0~40°C			
	Storage temperature	-10~60°C			
Environment	Operating humidity	20~80% RH Non-condensing			
	Storage humidity	10~60% RH Non-condensing			
·	Maximum operating time	18 hours /day			
	Operating system	Android 11			
	Processor	RK3568, quad-core			
	RAM	4G			
	ROM	32G			
Functions	Decoding resolution	1080P UHD compatible			
	Playback mode	Support loop, inter-cut, timer, shim, etc.			
	Touch support	No touch or 20 Points IR Touch			
	Supported Video Files	AVI, MPEG4, WMV, MKV, FLV, MP4, MOV			
	Supported Photo Files	JPG, JPEG, BMP, PNG, GIF			

Functions	Audio output, supported files	Left and right audio channel, MP3			
	RTC (real-time clock)	Yes			
	Schedule power on/off	Yes			
	System update	USB compatible			
	App installation	Support download and installation			
	TF	N/A			
	Ethernet (RJ45)	1			
	HDMI	1			
I/O interfaces	VGA	N/A			
	3.5mm headphone	N/A			
	USB	3			
	WiFi	1			
	Type-C OTG	N/A			
	SIM	N/A			
Structure	Net weight	No touch:47kg IR Touch:50kg			
	Gross weight	No touch:58kg IR Touch:61kg			
	Unit dimensions (W*D*H)	No touch:620*43*1760mm IR Touch:620*58*1760mm			
	Package dimensions (W*D*H)	No touch≈1850*200*740mm IR Touch≈1850*215*740mm			
	Shell material	Aluminum profile/sheet metal			
	Shell color	Black			
Language	OSD	English/Simplified Chinese			

Troubleshooting the Digital Signs – DF043NLB,DF043TLB				
Issue	Probable Cause	Solutions		
No picture or sound	 Unit not plugged into wall outlet Power cord not properly connected to the terminal on the back of the unit. Unit not powered on Wall outlet not working 	 Check that the unit is plugged into wall outlet. Confirm that the power cord is connected to the terminal on the back of the unit. Turn the on/off toggle switch located on the back of the unit, lower center, to the "on" position. Unplug unit, wait 20 seconds, plug unit back into outlet and try again. Make sure that outlet is working by plugging in a different electrical device. If all of the above have been checked and the issue is not resolved, contact a customer service representative. 		
 No sound (but picture is working) 	 Volume not adjusted on the remote control. Content/Video does not have sound. Content format is not compatible. Speakers do not work. 	 Adjust volume using the remote control Confirm content is one of the following compatible formats: AVI, MPEG4, WMV, MKV, flv, MP3, MP4, MOV. If unit is connected to Wi-Fi, go to YouTube and play video that has sound Unplug unit, wait 20 seconds, plug unit back into outlet and try again. Try playing the content on a different device (smart phone, computer or tablet) If all of the above have been checked and the issue is not resolved, contact a customer service representative. 		
 No picture (but sound is working) 	 Content file damaged. Content format is not compatible. Screen damaged or defective. 	 Confirm content is one of the following compatible formats: AVI, MPEG4, WMV, MKV, flv, MP3, MP4, MOV. Try playing the content on a different device (smart phone, computer or tablet) Unplug unit, wait 20 seconds, plug unit back into outlet and try again. If all of the above have been checked and the issue is not resolved, contact a customer service representative. 		
 Remote control not working 	 Batteries not inserted properly. Batteries are dead. Standing too close or too far from the unit. 	 Check that battery is inserted properly with positive and negative orientation. Insert new batteries. Stand within 1 foot of the front of the unit and point the remote directly at the sensor (green dot) If all of the above have been checked and the issue is not resolved, contact a customer service representative. 		

 No Wi-Fi signal 	 Wi-Fi is not turned on in product settings. 	 Check that Wi-Fi is turned on in settings O Click the settings icon from the
	 Wi-Fi is not connected to a network Low or no signal from the router Antenna is missing or not pointed upward. Damaged PC board 	 Android home screen. Click "Wi-Fi". Click the on/off icon in the upper right hand corner to turn on Wi-Fi. O" "On" will appear on the upper left hand side. Then select your Wi-Fi network Confirm that the antenna is in place and pointed upward. Check that other devices are not receiving the signal. If other devices are not receiving the Wi-Fi signal, please contact your internet service provider. Unplug or reset the router and wait for 20 seconds. Restart the router and check. If all of the above have been checked and the issue is not resolved, contact a customer
		service representative.
 Parts missing or Damaged 	 Parts missed during manufacturing. (No charge for replacements) Parts lost or damaged by the customer. (There is charge for replacements) 	 Contact a customer service representative.
 Having problems with installing software or getting content to play 	 Did you purchase the DisplayIt!Xpress software from Displays2go? Did the customer purchase or downloaded another 3rd party software onto the product? 	 If you purchased DisplayIt!Xpress software from Displays2go or from Best Wave directly, please contact Best Wave at support@bestwave. com or (480)368-8900 ext. 2 If you purchased or downloaded another 3rd party software onto the product, please contact the 3rd party software company's customer support for assistance.
 Cannot upload content 	 Content files are too large. Port being used is defective App being used to play content is 	 Confirm content is one of the following compatible formats: AVI, MPEG4, WMV, MKV, flv, MP3, MP4, MOV. Confirm file size is less than available space. If all of the above have been checked and the issue is not resolved, contact a customer service representative.
 Issues using pre-installed apps 	 Mistake in storing content to NAND Flash (shown on pg. 11) App is defective Android board is defective. 	 DiViEX App steps Explorer > Select USB > Select Multi > highlight files > Editor > Select Copy > Home > NAND > MediaFolder > Images> Editor > Paste Open DiViEX app and select desired

trasitions, slide time and looping >
Play
□ MX Player steps > Follow same steps as DiViEX
App > MediaFolder > Video > Editor > Paste.
 Open MX Player and select video to
play.
 Loop video: While the video is
playing, click on the video and there
should be 3 dots in the top right
corner. Click on the 3 dots > play >
check desired Loop option
If all of the above have been checked and
the issue is not resolved, contact a customer
service representative.

Cleaning and Maintenance

- 1. Avoid strong vibration or impact on the product.
- 2. Keep the product dry to avoid possible damage by moisture.
- 3. Don't place the product under direct sunlight which may shorten the service life of the screen.
- 4. Clean screen and product by using a glass cleaner.

5. If the product will not be used for a long time, pull out the power cord to prevent the internal short circuit or other potential dangers.

Names and Contents of Toxic and Hazardous Substances or Elements in the Product

Davit name	Toxic and hazardous substances or elements					
Part name	Pb	Hg	Cd	Cr ⁶⁺	PBB	PBDE
Display		0	0	0	0	0
Shell	0	0	0	0	×	×
Circuit board assembly *		0	0	0	0	0
Wires	0	0	0	0	0	0
Metal parts	0	0	0	0	0	0
Packaging materials*	0	0	0	0	0	0
Remote control		0	0	0	0	0
Speaker		0	0	0	0	0
Accessories*	0	0	0	0	0	0

*: Circuit board assembly includes PCB and the electronic elements thereof,

Packaging materials include packaging box, styrofoam, etc.,

Other accessories include instruction manual.

O: the content of the toxic and hazardous substances or elements in the part is lower than the limit specified in GB/T 26572-2011 standard.

 \times : the content of the toxic and hazardous substances or elements in the part is higher than the limit specified in GB/T 26572-2011 standard.

The table shows that the machine contains harmful substances inside. The data is provided by material suppliers and verified by the company according to the material type. Some materials contain harmful substances that can't be replaced in present technology. We are dedicated to improving this.

The EFUP of the product is ten years. The pollution control label is shown on the right.

The EFUP is valid only when the user operates in the normal conditions specified in the manual herein.

Waste Electrical and Electronic Products Recycling and Disposal Regulations

To protect the earth, if you do not need this product or its service life expires, please abide by your local *Waste Electrical and Electronic Products Recycling and Disposal Regulations* or send it to qualified local manufacture for recycling.

This Manual is for reference only and is subject to change without prior notice.

FCC STATEMENT:

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. Consult the dealer or an experienced radio/TV technician for help.

FCC Radiation Exposure Statement:

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated

with minimum distance 20cm between the radiator & your body.