

Bluetooth Headphone SBKO 4.0 C1 USER MANUAL SILVER CREST FCC ID: 2AJ9O-SBKO40C1	Table of contents 1 Introduction 1 2 Package content 1 3 Connection diagram 2 4 The way to change earhook 2 5 How to use 2 5.1 General functions 2 5.2 Pairing to mobile phone 4 5.3 Charging your device 5 6 Technology specification 6 7 After-sales service and support 6 8 FAQ 7 9 WARNING 8	C5 USER MANUAL 1.Introduction Thank you for choosing the Stereo Ear Buds. This manual will help you operate the Ear Buds, but you should first familiarize yourself with the Bluetooth functionality of your mobile phone or other devices before using the Ear Buds. Safety Rules 1\ Please follow the rules depicted in this manual closely to ensure your safety. Before using this Ear Buds, we would strongly encourage you to read through this user manual. 2\ Be more wary of any edges, uneven surfaces, metal parts, accessories and its packaging so as to prevent any possible injury or damage. 3\ Do not modify, repair or dismantle this Ear Buds. Doing so may result in fires, electric shocks, complete breakdown of this Ear Buds, etc. All of which, are not covered under warranty. 4\ Do not use any diluents or volatile liquid to clean the Ear Buds 5\ Do not use the Ear Buds in a hazardous location. 2.package content 1X Wireless Ear Buds C5 1X USB Charger cable 1X User Manual	C5 USER MANUAL 3.Connection Diagram right left Turn on/Play / pause/Turn off / Answer call/ End call/ Reject call/ Transfer call voice Last number redial Next /Volume up Previous/Volume down USB MIC 4.The way to change earhook 5.How to use 5.1.General Functions <table><tr><th>Desired Result</th><th>Required Action</th></tr><tr><td>Turn on</td><td>Press the “Ⓢ” button for 3 seconds when the device is off. (Red LED slowly flashes and a tone voice beeps)</td></tr><tr><td>Enter the pairing mode</td><td>When the device is off, Press the “Ⓢ” button for 6 seconds. (Blue LED and Red LED quickly flash alternately with two beep tone voice).</td></tr><tr><td>Pairing</td><td>In pairing Mode use a Bluetooth function mobile phone or other Bluetooth Master Device and to perform pairing action (detail refer to the chapter about pairing)</td></tr></table>	Desired Result	Required Action	Turn on	Press the “Ⓢ” button for 3 seconds when the device is off. (Red LED slowly flashes and a tone voice beeps)	Enter the pairing mode	When the device is off, Press the “Ⓢ” button for 6 seconds. (Blue LED and Red LED quickly flash alternately with two beep tone voice).	Pairing	In pairing Mode use a Bluetooth function mobile phone or other Bluetooth Master Device and to perform pairing action (detail refer to the chapter about pairing)	C5 USER MANUAL <table><tr><th>Desired Result</th><th>Required Action</th></tr><tr><td>Play / pause</td><td>Short click “Ⓢ” to play when the device is pausing and short click “Ⓢ” to pause when the device is playing.</td></tr><tr><td>Next / Volume up</td><td>Short press the “+” button for Next music Long press the “+” button for Volume up</td></tr><tr><td>Previous / Volume down</td><td>Short press the “-” button for Previous music Long press the “-” button for Volume down</td></tr><tr><td>Turn off</td><td>Press the “Ⓢ” button for 3 seconds when the device is on. (A tone voice beep and all LED is off)</td></tr><tr><td>Low battery warning</td><td>The Red LED flash</td></tr><tr><td>Charging</td><td>Plug the charger to port of the device. (Red LED is on)</td></tr><tr><td>Answer call</td><td>Short Press the “Ⓢ” button while a call coming</td></tr><tr><td>End call</td><td>Short Press the “Ⓢ” button while on going call</td></tr><tr><td>Transfer call voice</td><td>Double Press the “Ⓢ” button to transfer the call voice between the mobile phone and device while on going call</td></tr><tr><td>Reject call</td><td>Press the “Ⓢ” button for 1~2 seconds to reject call when the call is ringing</td></tr><tr><td>Battery power indication</td><td>Battery status will be shown on the top right corner of the phone screen after connected. (Only support iphone, iPad)</td></tr><tr><td>Enable/Disable Multipoint</td><td>Short press the “Ⓢ” button to enable Bluetooth at pairing mode Double press the “Ⓢ” button to disable the Multipoint at pairing mode</td></tr></table>	Desired Result	Required Action	Play / pause	Short click “Ⓢ” to play when the device is pausing and short click “Ⓢ” to pause when the device is playing.	Next / Volume up	Short press the “+” button for Next music Long press the “+” button for Volume up	Previous / Volume down	Short press the “-” button for Previous music Long press the “-” button for Volume down	Turn off	Press the “Ⓢ” button for 3 seconds when the device is on. (A tone voice beep and all LED is off)	Low battery warning	The Red LED flash	Charging	Plug the charger to port of the device. (Red LED is on)	Answer call	Short Press the “Ⓢ” button while a call coming	End call	Short Press the “Ⓢ” button while on going call	Transfer call voice	Double Press the “Ⓢ” button to transfer the call voice between the mobile phone and device while on going call	Reject call	Press the “Ⓢ” button for 1~2 seconds to reject call when the call is ringing	Battery power indication	Battery status will be shown on the top right corner of the phone screen after connected. (Only support iphone, iPad)	Enable/Disable Multipoint	Short press the “Ⓢ” button to enable Bluetooth at pairing mode Double press the “Ⓢ” button to disable the Multipoint at pairing mode	C5 USER MANUAL <table><tr><th>Desired Result</th><th>Required Action</th></tr><tr><td>Factory reset</td><td>Long press “+” button for 6 seconds at pairing mode to clear the paired device list.</td></tr><tr><td>Last number redial</td><td>Double click “Ⓢ” button on connect state.</td></tr></table> 5.2.Pairing to Mobile phone or other device To use your Ear Buds , you must first pair your Ear Buds with a phone or a computer. Once your Ear Buds is paired to a specific mobile phone, they will remain paired and automatically recognize each other whenever they are within range. Pairing to a phone and Entertainment: - Turn on your phone and ensure its Bluetooth function is activated - Turn on the Ear Buds go to the paring mode. - Search your Bluetooth devices on your phone by following the phone's instructions. Refer to your phone's user manual for more information. - After a few second the phone will list the device as a discover device. Select it and follow your phone instruction to select this pairing. - Then your phone will request a passkey or PIN, enter 0000 as your PIN or passkey. - Your phone will confirm the pairing, and then press Yes/Ok. - Finally, select to connect with device from your phone. - You can play music; watch TV/movie and play game with your phone, then you can hear all the sound or music form the device. Also you can control the player by operating the device. Example, volume up and next music.	Desired Result	Required Action	Factory reset	Long press “+” button for 6 seconds at pairing mode to clear the paired device list.	Last number redial	Double click “Ⓢ” button on connect state.	C5 USER MANUAL Pairing to a computer and Entertainment: - If there is no Bluetooth function supported by your computer, a Bluetooth adapter is necessary. Fix the adapter with your computer and ensure its Bluetooth function is activated. - Turn on the device and go to the paring mode. - Open the Bluetooth software (such as BlueSoleil) installed on your computer, and selects “Search your Bluetooth devices” function. Refer to user manual of the Bluetooth software for more information. - After a few second the “ device name” will list in Bluetooth software of your computer as a discover device. - Select this icon and click right button of mouse to select “pairing” item, then select “connect with audio device” with same operation. - Open your media player to play music, watch TV/move and play game, then all the sound will be playback on your device. 5.3.Charging your device The device is convenient to connect to AC charger or a USB charger with Micro USB port marked with . Make sure that your device is full charged for at least 6 hours before initial use. Insert one terminal of your charger to AC main or USB port of PC and other terminal to Micro USB. While charging, the red LED light constantly. When charging is completed, the indicator LED turns red to blue.	C5 USER MANUAL Warning: - You must select a qualified charger from a regular manufacturer. - You must charge the Ear Buds if it has been not used for more than 12 months. - Please don't use the USB charger on any other phone jack device 6.Technical specification <table><tr><th>Parameter</th><th>Value</th></tr><tr><td>Bluetooth Specification</td><td>Bluetooth 4.1</td></tr><tr><td>Bluetooth Profile</td><td>HFP1.6/A2DP1.2/AVRCP1.4/HSP1.2</td></tr><tr><td>RF Range</td><td>10 m</td></tr><tr><td>Frequency Response</td><td>180Hz-20KHz</td></tr><tr><td>Receiver Output</td><td>10mW</td></tr><tr><td>Signal-To-Noise</td><td>≥90dB</td></tr><tr><td>Distortion</td><td>≤3.0%</td></tr><tr><td>Playback Time</td><td>About 5.5 Hours</td></tr><tr><td>Charging Time</td><td>About 80 min</td></tr><tr><td>Dimension(L×W×H)</td><td>661.4X24X29.5mm</td></tr><tr><td>Weight</td><td>15.5g</td></tr></table> 7.After-sales service and support If your device is not performing as it should, please take it to your local service providers or dealer for service.	Parameter	Value	Bluetooth Specification	Bluetooth 4.1	Bluetooth Profile	HFP1.6/A2DP1.2/AVRCP1.4/HSP1.2	RF Range	10 m	Frequency Response	180Hz-20KHz	Receiver Output	10mW	Signal-To-Noise	≥90dB	Distortion	≤3.0%	Playback Time	About 5.5 Hours	Charging Time	About 80 min	Dimension(L×W×H)	661.4X24X29.5mm	Weight	15.5g	C5 USER MANUAL 8.FAQ 1\Why is there no power even when the Ear Buds is power on? Ans: Ensure the battery is being charged up to 6 hours for first time using. The LED is lighted when it starts charging. 2\There is no sound when playback. Ans: Check the connection between your device with phone or computer, if the connection is not established, please reconnect again. Make sure the Ear Buds is paired and connected with your target phone or other master device. 3\How can I know the Ear Buds has been fully charged? Ans: When the indicator LED turns red to blue when it is charging, it has been fully charged. 4\why the Ear Buds cannot connect with second phone? Ans: Please set the Ear Buds to multipoint mode. Connect the Ear Buds to phone A, Once again enter to pairing mode (phone one, will disconnect), and connect the Ear Buds to phoneB. and then use phone A paired device list to reconnect to the Ear Buds .	C5 USER MANUAL WARNING: This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following MEASURES: - Reorient or relocate the receiving antenna. - Increase the separation between the equipment and receiver. - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. - Consult the dealer or an experienced radio/TV technician for help. FCC RF warning statement: The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.
	Desired Result	Required Action																																																																							
	Turn on	Press the “Ⓢ” button for 3 seconds when the device is off. (Red LED slowly flashes and a tone voice beeps)																																																																							
	Enter the pairing mode	When the device is off, Press the “Ⓢ” button for 6 seconds. (Blue LED and Red LED quickly flash alternately with two beep tone voice).																																																																							
	Pairing	In pairing Mode use a Bluetooth function mobile phone or other Bluetooth Master Device and to perform pairing action (detail refer to the chapter about pairing)																																																																							
	Desired Result	Required Action																																																																							
	Play / pause	Short click “Ⓢ” to play when the device is pausing and short click “Ⓢ” to pause when the device is playing.																																																																							
	Next / Volume up	Short press the “+” button for Next music Long press the “+” button for Volume up																																																																							
	Previous / Volume down	Short press the “-” button for Previous music Long press the “-” button for Volume down																																																																							
Turn off	Press the “Ⓢ” button for 3 seconds when the device is on. (A tone voice beep and all LED is off)																																																																								
Low battery warning	The Red LED flash																																																																								
Charging	Plug the charger to port of the device. (Red LED is on)																																																																								
Answer call	Short Press the “Ⓢ” button while a call coming																																																																								
End call	Short Press the “Ⓢ” button while on going call																																																																								
Transfer call voice	Double Press the “Ⓢ” button to transfer the call voice between the mobile phone and device while on going call																																																																								
Reject call	Press the “Ⓢ” button for 1~2 seconds to reject call when the call is ringing																																																																								
Battery power indication	Battery status will be shown on the top right corner of the phone screen after connected. (Only support iphone, iPad)																																																																								
Enable/Disable Multipoint	Short press the “Ⓢ” button to enable Bluetooth at pairing mode Double press the “Ⓢ” button to disable the Multipoint at pairing mode																																																																								
Desired Result	Required Action																																																																								
Factory reset	Long press “+” button for 6 seconds at pairing mode to clear the paired device list.																																																																								
Last number redial	Double click “Ⓢ” button on connect state.																																																																								
Parameter	Value																																																																								
Bluetooth Specification	Bluetooth 4.1																																																																								
Bluetooth Profile	HFP1.6/A2DP1.2/AVRCP1.4/HSP1.2																																																																								
RF Range	10 m																																																																								
Frequency Response	180Hz-20KHz																																																																								
Receiver Output	10mW																																																																								
Signal-To-Noise	≥90dB																																																																								
Distortion	≤3.0%																																																																								
Playback Time	About 5.5 Hours																																																																								
Charging Time	About 80 min																																																																								
Dimension(L×W×H)	661.4X24X29.5mm																																																																								
Weight	15.5g																																																																								