

385mm

55mm

83mm

QCY | EMIE

QQ1000

Overview

Volume Indicator

Volume Band

MFB

LED

USB Port

Mic

How to Connect

Hold MFB for 2s to power on and pairing mode will be auto triggered(LED blinks red and blue promptly). On cellphone, search for "QQ1000" and tap to connect.

Notes: Last device in pairing records will be auto connected once the speaker is powered on. (Bluetooth on the device needs to be turned on and records in the speaker should not be deleted.)

How to Charge

Low battery will be warned by red blinking LED and voice prompt.

If you charge it when powering on, breathing LED will be solid blue.

If you charge it when powering off, breathing LED will be solid red and turn off once fully charged.

Volume Control

When playing music or calling, rotate Volume Band clockwise to turn up volume while counter clockwise to turn down volume

Power On/Off

Hold MFB for 2s to power on

Hold MFB for 5s to power off

Ignore Call

Hold MFB to ignore incoming call(LED blinks blue promptly)

Answer/End Call

Tap MFB to answer incoming call (LED blinks blue promptly) and tap it again to end the call

Switch Audio Output

When calling, hold MFB for 1s

Redial

When playing music or standby, double tap MFB to redial last call

Notes: last call dialing out may vary with different phone's system

Mute On/Off

When calling, tap MFB to switch on/off mute

Erase Pairing Records

Turn off the speaker, hold MFB for 5s when charging

Play/Pause Music

In standby, tap MFB to play/pause music

Pairing Between Speakers

If you hope to enjoy stereo, please purchase another QQ1000 to pair with your old one

Stereo Mode - Auto Pairing (Maiden Use)

1. Turn off both speakers, hold MFB on either speaker for 2s to power on and pairing mode will be auto triggered(LED blinks red and blue promptly)

2. On cellphone, search for "QQ1000" and tap to connect

3. Hold MFB on the other speaker for 2s to power on and two speakers will be auto paired soon with voice prompt

Notes: the speaker pairing with cellphone first will be deemed as master speaker while the other one slave speaker. Every operation on single speaker will be in sync with the other one(yet when calling, you may only use the master one)

Stereo Mode - Manual Pairing
(When you fail to enjoy auto pairing)

1. Power off both speakers, then hold MFBs on both speakers at the same time for 5s or until LED blinks red and blue with voice prompt.

2. After pair completed, on cellphone, search for "QQ1000" and tap to connect

Notes: the speaker paired with cellphone first will be deemed as master speaker while the other one slave speaker. Every operation on single speaker will be in sync with the other one(yet when calling, you may only use the master one)

2. No other pairing is able to proceed when two speakers are pairing with each other

Feature

Bluetooth 4.2 chip brings about better hifi experience than ever

It feels tough and skin-friendly with ABS & PC alloy shell

950mAh li-ion battery provides up to 10 hours of music

Basic Parameter

Model: QQ1000

Operation Range: 10m

Talk Time: 5 to 10hr

Battery Type: li-ion

Bluetooth Profile: HFP/A2DP/HSP/AVRCP

Bluetooth Version: V4.2

Weight: 253g

Charging Time: approx. 3hr

Battery Capacity: 3.7V 950mAh

Input Parameter: 5V±500mA

Size: 93.8×65.3×73.7mm

For after-sales service, please contact local distributor

Perform Stand: Q/HL 1-2016

URL: en.qcy.com

Supervisor: Shenzhen EMIE Technology Co.,Ltd

Address: 3rd.floor No.5 Building Anhua Industrial Zone Tairan Six Road Fu'tian District Shenzhen

Manufacturer: Dongguan Hele Electronics Co., Ltd

Address: Dalingya Industrial Zone, Daojiao Town, Dongguan City, Guangdong(QCY Environmental Zone No.5 Dalingya Area Yuehui Road)

After Service & Supports:

1. Warranty Period

1)Returning: 1 year after you purchase this item.

2)Repairing: 2 years after you purchase this item.

2. Free Returning will Only be Accessed under All of Following Circumstances

1) 1 year after you purchase this item.

2)Three completed guarantee receipts have to be provided to distributor(item model No., sales date and item serial No. shall be displayed on invoice and warranty card).

3)Required item has to be with full package and accessories.

4)Malfunction has to be caused by quality deficiencies.

Notes: Exchanged item will have the same model No. and spec. as your required one's.

3. Free Repairing will Only be Accessed under All of Following Circumstances

1) 2 years after you purchase this item.

2)Three completed guarantee receipts have to be provided to distributor(item model No., sales date and item serial No. shall be displayed on invoice and warranty card).

3) Malfunction has to be caused by quality deficiencies.

Free repairing & returning will not be accessed under following circumstances

A: Item is out of warranty period or effective sales receipt and warranty card fail to be provided.

B: Breakdowns of housing, bags, gifts and accessories or any non-functional fault.

C: Unauthorized disassembly, breakdowns caused by improper operation or using in environment which is forbidden in user's manual.

D: Artificial damages(including but not limiting to leaking damaged, dropping off, squeezing, breaking, burning and distortion).

E: Faults caused by force Majeures(such as earthquake, fire and flood).

Hazardous substances and their contents in the item

Part Name	Hazardous Substances					
	(Pb)	(Hg)	(Cd)	(Cr(VI))	(PBB)	(PBDE)
Main body	X	○	○	○	○	○
Battery	○	○	○	○	○	○
Ear tips	○	○	○	○	○	○
Accessories	○	○	○	○	○	○
Charging cable	X	○	○	○	○	○

This form is made by SJ/T 11364 regulation.

O: means that hazardous substance content in the homogeneous materials of this part is within the limitsof GB/T 26572 regulation.

X: means that hazardous substance content in, at least,one certain homogeneous material of this part is beyond the limits of GB/T 26572 regulation.

Lifespan:

As the booklet states, the eco-lifespan of the item is 5 years while using it in normal ways. During the period, no dangerous material will be leaked. The item must be recycled by the local law.

Notes:

Please arrange using time properly as your hearing may be damaged by using the device for a long time.

Tips

1. Before using the headset, please read the manual carefully and keep it for future references.

2. The headset need to be fully charged prior to first-time use.

3.If the headset is left unused for over two weeks, please recharge it periodically.

4. Please use the chargers made by qualified manufacturer.

5. If the headset cannot be found by your phone, please check whether it is in pairing mode; if left unconnected for a long while, the headset will exit pairing mode; please re-enter the mode; if a procedure error of your phone occurs, reboot it; if a procedure error of the headset occurs, reboot or reset it.

6. If the two units can not connect with each other automatically when switched on. Please hold the MFB of both units until the white light is on then move them approaching each other and wait for the connection completed.

Caution

1. Never disassemble or modify your headset for any reasons to avoid any damages and danger.

2. Do not store the headset in extreme temperatures (under 0°C or over 45°C).

3. Avoid using the indicator close to the eyes of children or animals.

4. Do not use this headset during a thunderstorm to avoid irregular function and increased risk of electric shock.

5. Do not use harsh chemicals or strong detergents to clean the headset.

6. Keep the headset dry.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-- Reorient or relocate the receiving antenna.

-- Increase the separation between the equipment and receiver.

-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Bluetooth

Recycle

No Fire

CE

CCC

RoHS

Trouble Shooting

When playing music in stereo mode, following questions may occur once your cellphone receives incoming call:

Q1: Why the master speaker disconnects with cellphone or slave speaker?

A1: They will auto reconnect with each other in 20s. Otherwise, please pair them manually

Q2: Why I can't hear anything even playing music?

A2: Re-tap MFB or Play Button on cellphone to resume playing

Q3: Why music can't be played continuously?

A3: Please re-start speakers

Notes: Occuring chance of the defects is cellphone dependent. However, if your cellphone is with no compatible issues, the defects will never happen

材质：105g哑粉，专色印刷